ULTIMATE POWER SOLUTION (FZC) The world's best dealer on Diesel Power Generation, Control Systems & Power Solution				
POWERED B	Y & Perkins LEROY-SOMER L	IPS CER	TIFIED BY	ISO ISO
		•	23/9	
230 KVA 3 PHASE 50Hz			60Hz	250 KVA 3 phase
GENERATING SET MODEL UPS P 230			ALTERNATOR DATA	
Output Ratings	Prime	Standby	Make	UPS/ Leroy Somer
380-415 V, 3 ph, 50 Hz, 1500 rpm	230 KVA	236 KVA	Model	UPS274G/ (TAL)046C
	184 KW	189 KW	No. of Bearings	1
380-415 V, 3 ph, 60 Hz, 1800 rpm	248 KVA	250 KVA	Insulation class	Н
	198 KW	202 KW	Wires	6/12
ENGINE/ TECHNICAL DATA			Ingress Protection	IP23
		Ratings at 0.8 Power Factor	Excitation System	Shunt
Engine Make	DE	-	Winding Pitch	2/3
Engine Make	PERKINS			
Engine Model	1206A-E70TTAG2		Overspeed	2250 mn ⁻¹
Governing Type	Electronic		Voltage Regulation (steady) ±1%
Number of Cylinders	6		CONTROL PANEL	
Cylinder Arrangement	Vertical in line		Make	DeepSea
Bore and Stroke mm	105 X 135		Model	7000 Series
Displacement/ Cubic Capacity litres	7.01		The DSE 7000 series is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software. Metering and Alarm Indications: Generator frequency Underspeed, Overspeed Generator volts (L-L-L-N) Generator current	
Induction System	Turbocharged aftercooled			
Cycle	4 stroke			
Combustion System	Direct Injection			
Compression Ratio	15.8:1			
Frequency and Engine Speed	50Hz & 1500rpm 60Hz & 1800rpm			
Gross Engine Power kW(hp)	204.2(273.7)	216.6(493)	Engine oil pressure Engine coolant temperature Hours run counter Battery volts	
Fuel Consumption @50% load L/hr	25.5 27.8		Fail to start/stop	
@ 75% load L/hr @ 100% load L/hr	3840.4•Emergency stop5154.5•Failed to reach loading voltage/frequency		-	
G	~ '			

٠

٠

•

16

25

Charge fail Low DC Voltage CAN diagnostics and CAN fail/error

Image is for Illustrative purpose only

Total Lubrication System Capacity litres

Total Coolant Capacity (inc. radiator) litres

Exhaust Temperature: °C





13

25

STANDARD SPECIFICATIONS

230 KVA 50Hz **3 PHASE**

1. ENGINE

Perkins four stroke heavy duty high performance industrial type diesel engine.

2. ENGINE FILTRATION SYSTEM

- Cartridge type dry air filter.
- Two cartridge type fuel filter.
- Full flow lube oil filter. All filters have replaceable elements.

3. COOLING RADIATOR

Radiator and cooling fan, complete with safety guards designed to cool the engine at high ambient temperatures (consult your dealer for de-ration factors)

4. EXHAUST SYSTEM

Exhaust gas flow Maximum allowable back pressure

5. CIRCUIT BREAKER TYPE

3 pole MCCB. (4 pole is optional)

6. FUEL SYSTEM


The baseframe design is incorporated with an integral fuel tank with a capacity of approx.. 8 hours running at Full load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and the drain plug.

STANDARD GENERATOR DIMENSION AND WEIGHT

31..3 (m3/min)

18.0 (kPa)

Silent Type (with Soundproof Canopy)



7. ALTERNATOR

- 7.1 INSULATION SYSTEM
- The insulation system is Class H.
- All windings are impregnated in either a triple dip thermoset-Ting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polvester resin.
- Heavy coat of antitracking varnish additional protection Against moisture or condensation.

7.2 AUTOMATIC VOLTAGE REGULATOR (AVR)

The fully sealed Automatic Voltage Regulator maintains

The Voltage Regulation at ±1%. Nominal adjustment by means of a trim pot incorporated on the AVR.

8. MOUNTING ARRANGEMENT

8.1 COUPLING

The Engine and Alternator are directly coupled by means of an SAE flange. The Engine flywheel is flexibly coupled to the Alternator rotor

8.2 ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between tge Engine/Alternator feet and the Baseframe thus ensuring complete vibration isolation of the rotating assembly.

8.3 SAFETY GUARDS

The Fan & Fan Drive along with the battery Charging Alternator are Safety Guard protected for personnel protection.

250 KVA **3 PHASE**

9. FACTORY TEST

60Hz

- The Generating set is load tested before dispatch
- · All protective devise control functions and site load conditions are simulated. The generator and its systems are checked before dispatch.

10. EQUIPMENT FINISHING

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability

11. DOCUMENTATION

Operation & Maintenance manual, Circuit wiring diagrams and Commissioning/ Fault Finding instruction leaflets are accompanied with the Generator.

12. QUALITY STANDARDS

The equipment meets the following standards, BS4999, BS5000, BS5514 IEC 60034, VDE0530, NEMA MG 1.22 and ISO 8528

13. WARRANTY

All of the Generating sets are covered under a warranty policy For a period of 12 months or 1000 working hours. Warranty of the equipment is in line with manufacturers warranty terms & conditions. (check warranty statement for more details, as it may vary for different countries.)

In line with the continuous product development, we reserve The right to change specifications without notice.

