ULTIMATE POWER SOLUTION (FZC) The world's best dealer on Diesel Power Generation, Control Systems & Power Solution Powered BY Perkins LEROY-SOMER UDS CERTIFIED BY						
- Powered Bi	<b>Serkins</b>	LENOTSOWER UP:	<b>S</b>	TIFIED BY	Rohan	
350 KVA з рназе 50Hz				60Hz	400 KVA 3 PHASE	
GENERATING SET MODEL UPS P 350				ALTERNATOR DA	ТА	
Output Ratings	Prime		Standby	Make	UPS/ Leroy Somer	
380-415 V, 3 ph, 50 Hz, 1500 rpm	350 KVA		400 KVA	Model	UPS314F/LSA (TAL) 46H	
	280 KW		320 KW	No. of Bearings	1	
380-415 V, 3 ph, 60 Hz, 1800 rpm	400 KVA		438 KVA	Insulation class	Н	
	320 KW		350 KW	Wires	6/12	
ENGINE/ TECHNICAL DATA				Ingress Protection	IP23	
			Ratings at 0.8 Power Factor	Excitation System	Shunt	
Engine Make		PERKIN	-	Winding Pitch	2/3	
Engine Model	1706A-E93TAG2			Overspeed	2250 mn <sup>-1</sup>	
Governing Type	Electronic			Voltage Regulatio	n (steady) ±1%	
Number of Cylinders		6		CONTROL PANEL		
Cylinder Arrangement	Vertical in line		Make	DeepSea		
Bore and Stroke mm		115 X 149		Model	7000 Series	
Displacement/ Cubic Capacity litres	9.29			The <b>DSE 7000</b> series is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.		
Induction System	Turbocharged aftercooled					
Cycle	4 stroke					
Combustion System		Direct Injection			Metering and Alarm Indications: • Generator frequency	
Compression Ratio	16.5			Underspeed, Overspeed		
Frequency and Engine Speed		50Hz & 1500rpm	60Hz & 1800rpm	Generator volts (L-L-L-N) Generator current		
				Engine oil p Engine cool	ressure lant temperature	
Gross Engine Power kW(hp)	311.4(417.6) 325.8(436.9) • Hours run c • Battery volts			ounter		
Fuel Consumption @50% load L/hr		199 206 • Fail to start/stop				
@ <b>75% load</b> L/hr @ <b>100% load</b> L/hr		192197•Emergency stop190194•Failed to reach loading voltage/frequency				
Total Lubrication System Capacity litres		26	30	Charge fail Low DC Voltage		
Total Coolant Capacity (inc. radiator) litres		33	33	CAN diagnostics and CAN fail/error		

Image is for Illustrative purpose only

Exhaust Temperature: °C





# **STANDARD SPECIFICATIONS**

# 350 KVA 3 PHASE 50Hz

#### 1. ENGINE

Perkins four stroke heavy duty high performance industrial type diesel engine.

# 2. ENGINE FILTRATION SYSTEM

- Cartridge type dry air filter.
- Two cartridge type fuel filter.
- Full flow lube oil filter. All filters have replaceable elements.

#### **3. COOLING RADIATOR**

Radiator and cooling fan, complete with safety guards designed to cool the engine at high ambient temperatures (consult your dealer for de-ration factors)

#### 4. EXHAUST SYSTEM

Exhaust gas flow Maximum allowable back pressure

**5. CIRCUIT BREAKER TYPE** 

3 pole MCCB. (4 pole is optional)

#### 6. FUEL SYSTEM

The baseframe design is incorporated with an integral fuel tank with a capacity of approx.. 8 hours running at Full load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and the drain plug.

# STANDARD GENERATOR DIMENSION AND WEIGHT

1090.00


-885.00

225.00


31..3 (m3/min)

18.0 (kPa)

#### Silent Type ( with Soundproof Canopy)



**Open Type ( without Soundproof Canopy)** 



# 7. ALTERNATOR

- 7.1 INSULATION SYSTEM
- The insulation system is Class H.
- All windings are impregnated in either a triple dip thermoset-Ting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polyester resin.
- Heavy coat of antitracking varnish additional protection Against moisture or condensation.

#### 7.2 AUTOMATIC VOLTAGE REGULATOR (AVR)

The fully sealed Automatic Voltage Regulator maintains

The Voltage Regulation at  $\pm 1\%$ . Nominal adjustment by means of a trim pot incorporated on the AVR.

# 8. MOUNTING ARRANGEMENT

#### 8.1 COUPLING

The Engine and Alternator are directly coupled by means of an SAE flange. The Engine flywheel is flexibly coupled to the Alternator rotor.

#### 8.2 ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between tge Engine/Alternator feet and the Baseframe thus ensuring complete vibration isolation of the rotating assembly.

#### 8.3 SAFETY GUARDS

640.00

1300.05

300.00

-

0.00

3860.00

-740.00-

The Fan & Fan Drive along with the battery Charging Alternator are Safety Guard protected for personnel protection.

-890.00-

1380.00

1080.00

400.00

-150.00

-690.00

0

# 400 KVA 3 PHASE

# 9. FACTORY TEST

60Hz

- The Generating set is load tested before dispatch
- All protective devise control functions and site load conditions are simulated. The generator and its systems are checked before dispatch.

#### **10. EQUIPMENT FINISHING**

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability.

#### **11. DOCUMENTATION**

Operation & Maintenance manual, Circuit wiring diagrams and Commissioning/ Fault Finding instruction leaflets are accompanied with the Generator.

#### **12. QUALITY STANDARDS**

The equipment meets the following standards, BS4999, BS5000, BS5514 IEC 60034, VDE0530, NEMA MG 1.22 and ISO 8528.

### **13. WARRANTY**

-840.00-

All of the Generating sets are covered under a warranty policy For a period of 12 months or 1000 working hours. Warranty of the equipment is in line with manufacturers warranty terms & conditions. (check warranty statement for more details, as it may vary for different countries.)

In line with the continuous product development, we reserve The right to change specifications without notice.

3860.00

1090.00

-885.00

\$00.00

2000.00

380.00